

## PRODUCT DESCRIPTION

RFS' CDS\*-43 series of Directional Couplers have been designed for a variety of wireless applications in the frequency band from 555 to 6000MHz. The units couple off a defined fraction of a RF signal from 5 to 30 dB (depending on the model number) with minimal reflections or loss. The broad frequency range is ideally suited for multi-band distributed antenna systems or in combination with RADIAFLEX® radiating cables.



## FEATURES / BENEFITS

- **Broadband 555MHz-6000MHz**
- 4.3-10 Female Interface
- PIM Optimized Design (163dBc @2x43dBm)
- Low Insertion Loss
- High Power Handling
- Small Size, Low Weight

## TECHNICAL FEATURES

### ELECTRICAL SPECIFICATIONS

|                   |     |                                                              |
|-------------------|-----|--------------------------------------------------------------|
| Frequency Range   | MHz | 555-6000                                                     |
| VSWR              |     | 1.20:1@555-2700MHz, 1.25:1@2700-3800MHz, 1.30:1@3800-6000MHz |
| Power Rating      | W   | 300                                                          |
| PIM 3rd @2*43 dBm | dBc | 163                                                          |
| Input Impedance   | Ohm | 50                                                           |

### MECHANICAL SPECIFICATIONS

|                        |         |               |
|------------------------|---------|---------------|
| Connectors             |         | 4.3-10 Female |
| Number of Input Ports  |         | 1             |
| Number of Output Ports |         | 2             |
| Net Weight ±10%        | kg (lb) | 0.34 (0.75)   |
| Temperature Range      | °C      | -25 to +65    |
| IP Level               |         | IP66          |
| RoHS                   |         | Compliant     |

**CDS10-43-555/6000**

Broadband Directional Coupler for Wireless &amp; Indoor Application, 555-6000MHz, 10dB Coupling Loss

**MODEL NUMBER SPECIFICATIONS**

| Model Number       |         | <b>CDS5-43-555/6000</b>                                                 | <b>CDS6-43-555/6000</b>                                                 | <b>CDS8-43-555/6000</b>                              | <b>CDS10-43-555/6000</b>          |
|--------------------|---------|-------------------------------------------------------------------------|-------------------------------------------------------------------------|------------------------------------------------------|-----------------------------------|
| Coupling Loss      | dB      | 5.0                                                                     | 6.0                                                                     | 8.0                                                  | 10.0                              |
| Coupling Tolerance | dB      | 5.0±1.15                                                                | 6.0±1.2                                                                 | 8.0±1.2                                              | 10.0±1.25                         |
| Isolation          | dB      | 25@555-2700MHz<br>23@2700-3800MHz<br>21@3800-4900MHz<br>17@4900-6000MHz | 26@555-2700MHz<br>24@2700-3800MHz<br>22@3800-4900MHz<br>18@4900-6000MHz | 28@555-2700MHz<br>24@2700-4900MHz<br>22@4900-6000MHz | 30@555-2700MHz<br>26@2700-6000MHz |
| Insertion Loss     | dB      | 2.45                                                                    | 1.9                                                                     | 1.25                                                 | 0.8                               |
| Dimensions, L*W*H  | mm (in) | 156.5*60*29.5<br>(6.16*2.36*1.16)                                       | 156.5*60*23.5<br>(6.16*2.36*0.93)                                       | 156.5*60*23.5<br>(6.16*2.36*0.93)                    | 159*62*22<br>(6.26*2.44*0.87)     |

**MODEL NUMBER SPECIFICATIONS**

| Model Number       |         | <b>CDS13-43-555/6000</b>                             | <b>CDS15-43-555/6000</b>                             | <b>CDS20-43-555/6000</b>          | <b>CDS30-43-555/6000</b>                             |
|--------------------|---------|------------------------------------------------------|------------------------------------------------------|-----------------------------------|------------------------------------------------------|
| Coupling Loss      | dB      | 13.0                                                 | 15.0                                                 | 20.0                              | 30                                                   |
| Coupling Tolerance | dB      | 13.0±1.3                                             | 15.0±1.35                                            | 20.0±1.4                          | 30.0±1.55                                            |
| Isolation          | dB      | 33@555-2700MHz<br>30@2700-4900MHz<br>27@4900-6000MHz | 34@555-3800MHz<br>32@3800-4900MHz<br>28@4900-6000MHz | 38@555-4900MHz<br>32@4900-6000MHz | 46@555-2700MHz<br>43@2700-4900MHz<br>39@4900-6000MHz |
| Insertion Loss     | dB      | 0.6                                                  | 0.5                                                  | 0.3                               | 0.3                                                  |
| Dimensions, L*W*H  | mm (in) | 159*62*22<br>(6.26*2.44*0.87)                        | 159*62*22<br>(6.26*2.44*0.87)                        | 159*62*22<br>(6.26*2.44*0.87)     | 159*62*22<br>(6.26*2.44*0.87)                        |

**External Document Links**[LINK to VEX FILES](#)**Notes**